



ACCURACY

MIXER CONSOLE



F26-4

F series specialized for recording, stadium, Disco and radio station. its easy operation, 2 group, 7-band stereo band sub-woofer, phantom power, ultra-low-noise circuit design make F series suitable for any situations.

- ◆ Low noise. BG30 patent MIC pre-amplifier.
- ◆ Smooth and modern design.
- ◆ 16 kind ECHO.
- ◆ Sub-woofer output.
- ◆ 100 mm Japanese ALPS potentiometer.
- ◆ Germany SMT tech, TDK, PHILIPS, RUBYCON high quality components. Stable and high performance.
- ◆ High effect, energy-saving switch design. No interference.

SPECIFICATION :

- Inputs Sensitivity MIC: 60dB LINE: 20dB Eff Ret : -20dB Tape In : -20dB
- EFFECTS : ECHO 12ms-200ms
- Groups : 2
- Output Voltage : 4V Max
- S/N Ratio : > 85dB
- Less Than (THD) : 0.03% (1KHz Full Power)
- Frequency Response : 20Hz~20KHz ±3dB
- Headphone Output : 7V 220Ω
- Parametric EQ Hi: ±15dB/10KHz Mid: ±15dB/250Hz Low: ±15dB/80Hz
- Net Dimension : 89 x 10 x 40 cm
- Net Weight : 12 Kg
- Power Consumption / Voltage : 110 or 220V only / 50-60 Hz / 60W (F26/4)