

JA-S1



- Brand new JA-S1 is designed with Digital power output system.
- 200W x 2 channels output can connect 2 pair of LS-M50.
- Master Mic. Volume, Master Music Volume & Echo are in motor design. (R/C Optional)
- Balanced Input jack x 4 systems (2 x Mic., 2 x Audio),
- Sub Woofer Output jack x 2 systems (with / without low-pass filter)
- Slim body, pure & clear sound, with traditional Japan Karaoke echo effect.

- 全新设计的JA-S1是采用纯数码后级功放管系统,能减低热量.
- 每声道200瓦的强劲功率能同时连接两对LS-M50.
- 总话筒控件,总音乐控件和音效控件全设有摇控马达.(摇控器另配置)
- 平衡输入口4组(话筒2组,音源2组).
- 低频输出口2组(带/不带低通滤波器)
- 轻薄的机身,清纯的音质和传统日本卡拉OK的音效.

Specification 规格

Maximum Output Power	最大输出功率	200W + 200W
Total Harmonic Distortion	总谐波失真	0.05% (1 kHz, 50W)
Frequency Responses	频率响应	20Hz - 15kHz, +4/-2dB
Music	音乐	40Hz - 15kHz, +3/-3dB
Mic.	话筒	
Tone Control Characteristics	音调控制特性	
Music - Bass	音乐 - 低音	13/-10dB (100Hz)
- Mid	- 中音	±12dB (1kHz)
- Treble	- 高音	12/-10dB (10kHz)
Mic. - Bass	话筒 - 低音	±12dB (100Hz)
- Mid	- 中音	±12dB (1kHz)
- Treble	- 高音	10/-9dB (10kHz)
Speaker Impedance	扬声器阻抗	
Key Control Range	音阶控制范围	11级steps,半音half-tone
Power Voltage	电压	AC 220V 50 Hz
Power Consumption	电源消耗	110W
Dimensions (WxHxD)	尺寸	420 x 99 x 405 mm
Weight	重量	毛重 9kg